

W-8 Dual-mono Power Amplifier Specifications

Type	Solid State
Configuration	Dual-Mono / Fully Balanced
Power Supply Transformers	2 x 1.3kVA
Power Supply Capacitance	240,000 μ F
Class Of Operation	A/AB
Balanced Inputs	XLR - 1 pair
Single-ended Inputs	RCA - 1 pair
Input Device Type	J-FETs
Input Impedance	47.5 K Ω
Input Sensitivity	1260mV RMS
Output Device Type	Bipolars - 16 per channel
Output Binding Posts	WBT - 2 pairs
Output Power @ 8 Ω	250 Watts
Output Power @ 4 Ω	500 Watts
Output Power @ 2 Ω	1000 Watts
Output Power - Bridged Mono	1000 Watts
Frequency Response	10Hz - 200kHz (+0/-3dB)
Output Impedance	< 0.01
Damping Factor (static)	> 800
Gain	31dB
Signal-to-noise Ratio	106dB @ full power
Maximum Output Voltage	50 Volts
Slew Rate	42 V/ μ s
Maximum Current - Peak	64 amperes
Maximum Current - Continuous	26 amperes
Crosstalk @ 1kHz	-105dB
IMD	Unmeasurable
THD (20Hz - 20kHz @ 1 watt)	0.015 %
THD (20Hz - 20kHz @ 250 watts)	0.04 %
12 Volt Trigger Operation	Direct Logic (0V = off, 12V=on) using a 1/8" mini-jack with an input impedance of 1K Ω and current requirement of 12mA
RS-232 Port	9-pin female DB connector
Power Consumption @ idle	50 watts
AC Power Requirements	120V / 60Hz 240V / 50Hz
Fuse Replacement - 120V	10A long fast blow
Fuse Replacement - 230V	5A long fast blow
Shipping weight	92 lbs / 42 kgs
Dimensions (w x h x d)	18.8 x 7.4 x 17.5 in.

Features & specifications are subject to change without notice.